Firmware Updating

1. Connect the battery pack with computer. And run the 'BatteryMonitor' software.



2.Click the 'Firmware Update'. Choose the right Port number, Pack number, and the baudRate is 19200. Parity is None. DataBits is 8. StopBits is One. Then click 'Open'.

Port:	COM3	~	Pack Num:	Pack0	~
BaudRate:	19200	~			
Parity:	None	~			
DataBits:	8	~			
StopBits:	One	~	ෆ් Open	ວ	Reset
Program Up	date				
lease sele				B	, Downloa

Firmware Updat	te					×
Set						
Port:	COM3	~	Pack Num:	Pack0		~
BaudRate:	19200	~				
Parity:	None	~				
DataBits:	8	~				
StopBits:	One	~	් Close		C Reset	-
Program Up	date					
Please sele					😕 🛃 Dov	vnload
		0.	0%			
打开						×
→ ▼ ↑ <mark>]</mark> « 文档	> WeChat Files > shajie9	hao → FileStorage	> File > 2021-05	5 v	♀ 搜索*2021-05*	
织▼ 新建文件夹					811 -	
k 快速访问	名称	/			修改日期	类型
三 桌面 ★	CAN1101[FW27-UPSET_I	Default01_210511]-01	.ehex		2021/5/19 8:24	EHEX 戈
01-外包装尺寸						
C32206						
新建文件夹						
■此电脑						
🌶 网络						
۲						3
文件名(N	CAN1101[FW27-UPSET_[Default01_210511]-01	ehex	~	Program file(*.ehex	;*.hex)
					打开(0)	取消

3. Click the file icon. Choose updating firmware. And click 'Download'.

Port:	COM3	~	Pack Num	Pack0		~
BaudRate:	19200	~	, ack Hum.	Tucko		
Parity:	None	~				
DataBits:	8	~				
StopBits:	One	~	එ Close		'D Re	eset
rogram Up	date					
ease sele	:\Users\k083	2\Docume	nts\WeChat File	s\sh	5	Downl

4. Then the firmware will update automatically. After the firmware updated successfully, click 'OK'.

Port:	COM3	~	Pack Num:	Pack0		~
audRate:	19200	~				
Parity:	None	~				
DataBits:	8	~				
ton Rite	One	~	ථ Close		D Re	eset

🖳 Firmware U	pdate				-		×
– Set ——							
Port:	Info		- •			~	
BaudRa	Success						
Parity:							
DataBit							
StopBit						set	
- Progran			JK				
Please se		9.		· 11		ownlo	bad
		100					